

Oscilloscope



Features:

- 40MHz high bandwidth with 2 channels
- 100MSPS real time sampling rate
- Multi-language support, easy to use
- USB2.0 interface, no external power required
- 23 measurement functions, PASS/FAIL check, FFT
- OS: Windows NT, Windows 2000, Windows XP, Windows 7
- Labview/VB/VC SDK

Specifications:

	Model	72-10155
Acquisition	Sample Mode	Real-Time Sample
	Sample Rate	100MSPS
	Average	N acquisitions, all channels simultaneously, N is selectable from 1-128
Input	Input Coupling	DC, AC, GND
	Input Impedance	Resistance: 1M Ω ; Capacitance: 25pF
	PP-80,PP-150,PP-200 Probe Attenuation	10X
	Probe Attenuation Factors	1X, 10X
	Maximum Input Voltage	35Vpk (DC + peak)
Horizontal	Scanning Speed Range(Sec/Div)	4ns/div ~ 1h/div(1-2-4 sequences)
	Sample Rate and Delay Time Accuracy	± 50 ppm(any interval ≥ 1 ms)
	Wave form Interpolation	Step, Linear, Sin(x)/x
	Memory Depth(Sample Points)	10K : available all timebase; 32K : 40 μ s/div-400ms/div(Dual channel); 20 μ s/div-400ms/div(Signal channel); 64K : 40 μ s/div-400ms/div
Vertical	Analog Bandwidth	40MHz (-3dB)
	A/D converter	8 bit resolution
	Vertical Scale(Volt/div) Range	10mV ~ 5V/div @ x1 probe(1,2,5 sequence); 100mV ~ 50V/div @ x10 probe
	Position Range	± 4 division
	Selectable Analog Bandwidth Limit(typical)	20MHz
	Lower Frequency Response(-3dB)	≤ 10 Hz(at input BNC)
	Rise Time at BNC(typical)	≤ 8.8 ns
	DC Gain Accuracy	± 3 %



Oscilloscope



Trigger	Trigger Source		CH1,CH2, EXT
	Trigger Mode		Auto, Normal and Single
	Trigger Type		Edge trigger: Rising edge, falling edge.
	Trigger Sensitivity		0.02 div increments
	Trigger Level Range		±4V
	Trigger Level Accuracy		±4 division
Measurement	Cursor Measure		Amplitude difference between cursors (ΔV); Time difference between cursors (Δt); Reciprocal of Δt in Hertz ($1/\Delta t$) (Cross, Trace, Horizontal, Vertical)
	Auto Measure	Voltage	Vp-p, Vmax, Vmin, Vmean, Vamp, Vtop, Vbase, Vmid, Vrms, Vcrms, Preshoot, Overshoot
		Time	Frequency, Period, Rise Time(10%~90%), Fall Time(10%~90%), Positive Width, Negative Width, Duty Cycl
	Temperature		Operating: 0°C to 40°C Non-operating: -20°C to +60°C)
Environmental	Cooling Method		Forced air
	Humidity		Below +35°C, ≤90% relative humidity; +35°C to +40°C, ≤60% relative humidity
	Altitude		Operating: 3,000m or below; Non-operating: 15,000m or below
	Size		190mm(L)×100mm(W)×35mm(H)
Mechanical	Heavy		Without Packaged 0.29kg; Packaged 0.9kg;
	Probe		X1, X10 two passive probes. The passive probes have a 6MHz bandwidth (rated 100Vrms CAT III) when the switch is in the X1 position, and a maximum bandwidth (rated 300Vrms CAT II) when the switch is in the X10 position. Each probe consists of all necessary fittings
Accessories	USB Line		A USB A-B line, used to connect external devices with USB-B interface like a printer or to establish communications between PC and the oscilloscope.
	Installation CD		A software installation CD and it also contains the user manual for the Tenma Oscilloscope.

Part Number Table

Description	Part Number
Oscilloscope, PC, 2 Channel, 40MHz	72-10155

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

