



Specifications

Basic Functions	Range	Best Accuracy
DC Voltage	400 mV	$\pm (0.8\% + 3)$
	4 V / 40 V / 400 V	$\pm (0.8\% + 1)$
	1,000 V	$\pm (1\% + 3)$
AC Voltage	4 V / 40 V / 400 V	$\pm (1\% + 5)$
	750 V	$\pm (1.2\% + 5)$
DC Current	400 μ A / 4,000 μ A	$\pm (1\% + 2)$
	40 mA / 400 mA	$\pm (1.2\% + 3)$
	4 A / 10 A	$\pm (1.5\% + 5)$

Specifications

Basic Functions	Range	Best Accuracy
AC Current	400 μ A / 4,000 μ A	\pm (1.5% + 5)
	40 mA / 400 mA	\pm (2% + 5)
	4 A / 10 A	\pm (2.5% + 5)
Resistance	400 Ω	\pm (1.2% + 2)
	4 K Ω / 40 K Ω / 400 K Ω	\pm (1% + 2)
	4 M Ω	\pm (1.2% + 2)
	40 M Ω	\pm (1.5% + 2)
Capacitance	40 nF / 400 nF / 4 μ F / 40 μ F	\pm (3% + 5)
	100 μ F	\pm (4% + 5)
Frequency	10 HZ to 10 MHZ	\pm (0.1% + 3)
Special Functions		
Diode		✓
Duty Cycle		0.1% to 99.9%
Continuity Buzzer		✓
Data Hold		✓
Rel		✓
Low Battery Display		✓
Input Impedance for DC Voltage Measurement	Around 10 M Ω	✓
Max. Display	3999	✓
General Characteristics		
Power	9 V Battery (6F22)	
LCD Size	68.8 x 42 mm	
Product Colour	Red and Grey	
Product Size	177 x 85 x 44.2 mm	
Standard Accessories	Test Lead; Battery, English Manual; Alligator Clip Test Lead; CompactDisc; RS-232	
Optional Accessories	No	

Part Number Table

Description	Part Number
Multimeter, Digital	72-7735

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. TENMA™ is the registered trademark of the Group. © Premier Farnell plc 2011.