

Digital Clamp Meter



Specifications

Basic Functions	Range	Basic Accuracy
AC Voltage	15V / 100V / 300V / 600V	± (1.2% +5)
AC Current	40A / 100A / 400A / 1000A	± (2% +5)
Active Power	0.01kW-600kW	± (3% +5)
Apparent Power	0.01kVA-600kVA	± (3% +5)
Reactive Power	0.01kVAr-600kVAr	± (4% +5)
Power Factor	0.3 ~ 1 (Capacitive or Inductive)	± 0.022
Phase Angle	0°C ~ 360°C	± 1°
Frequency	20Hz - 500Hz	√
Active Energy	1 ~ 9,999kWh	± (3% +2)

Features

Auto Ranging	-	√
Single-phase 2-wire	-	√
3-phase 3-wire	-	√
3-phase 4-wire	-	√
True RMS	AC Voltage or Current	√
Calibration Feature	-	√
Data Logging	99	√
Data Recall	-	√
Max / Min Mode	-	√
Data Hold	-	√
USB	-	√

Digital Clamp Meter



Features		
Basic Functions	Range	Basic Accuracy
Display Backlight	–	√
Full Icon Display	–	√
Sleep Mode	–	√
Low Battery Display	–	√
Input Impedance for AC Voltage Measurement	≥ 10MW	√
Max. Display	9,999	√
Analogue Bar Graph	–	√

General Characteristics	
Power	1.5V Battery (LR6) × 4
LCD Size	46mm × 42mm
Product Color	Orange and Grey
Product Net Weight	601g
Product Size	303mm × 112mm × 39mm
Standard Accessories	4pcs of Test Lead, Battery, English Manual, 4pcs of Alligator Clips, USB Interface Cable, Software, Tool Box
Standard Individual Packing	Gift Box
Standard Carton Measurement	480mm × 372mm × 315mm (0.056 CBM Per Standard Carton)
Standard Carton Gross Weight	12 kgs.

Part Number Table

Description	Part Number
Multimeter, Digital, Clamp	72-9490

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

